

## **ELECTRONIC THERMOSTAT**

## ETR 011



- > Large setting range
- > Small hysteresis
- > Status indicator (LED)
- > Change-over contact
- > Clip fixing

The electronic thermostat is used for controlling heating and cooling equipment, filter fans or signal devices. The thermostat registers the surrounding air and can switch both and inductive and resistive loads via relay with change-over contact. The LED integrated in the adjustment knob is lit when the NC is closed. (e.g. when a connected heater is operating).






















Switch difference	4K (± 1K tolerance) at +20°C (+68°F)	
Sensor element	NTC	
Reaction time	approx. 5 sec.	
Contact type	change-over contact (relay)	
Service life	> 50,000 cycles	
Max. switching capacity (relay output)	240VAC / 120VAC, 8 (1.6) A DC 100W at 24VDC	
Max. inrush current	AC 16A for 10 sec.	
Optical indicator	LED	
Connection	5-pole terminal, clamping torque 0.5Nm max.: rigid wire 2.5mm <sup>2</sup> stranded wire (with wire end ferrule) 1.5mm <sup>2</sup>	
Mounting	clip for 35mm DIN rail, EN 60715	
Casing	plastic according to UL 94V-0, light grey	
Dimensions	64.5 x 42 x 38mm	
Weight	approx. 70g	
Fitting position	vertical	
Operating/Storage temperature	-40 to +185°F (-40 to +85°C)	
Operating/Storage humidity	max. 95% RH (non-condensing)	
Protection type	IP20	


## Connection diagram






Filter fan, Cooling equipment, Signal device







Examples of connection

Art. No.	Operating voltage	Setting range	Approvals
01131.0-00	230VAC, 50/60Hz	-20 to +60°C	VDE + CSA-US
01131 9-00	120VAC 50/60Hz	-4 tn +140°F	CSA-US